

## PRODUCT DATA SHEET

### Lost Duo 1514mm - T16 2x80W

**DESIGN BY :**

Ernesto Gismondi

**MATERIALS :**

Aluminium

**DESCRIPTION :**

Single pendant with direct-indirect lighting using 54W and 80W T16 fluorescent light source. 2 versions: lost (1xT16) and lost duo (2xT16). Dark light optics with lateral aluminium reflectors. Aluminium central profile (lost duo). End caps in translucent injection moulded polycarbonate. Light output ratio: 66%. Light distribution: 55% indirect and 45% direct. Electronic control gear, with or without dimming (DALI-SWITCHDIM). Luminaire comes complete with quick-adjustment steel cables, ceiling surface plate and power cable. Complies with standard EN60598-1 and other specific standards.

**LOST DUO**

For use with 2x54W or 2x80W T16. Interactive-DALI system, combining a movement detector and a daylight sensor for auto-regulation in relation to people presence and variations in daylight. Emergency lighting.

**Light emission**

Indirect/direct Dark Light



### TECHNICAL DATA SHEET

**Features**

Product name:	Lost Duo 1514mm - T16 2x80W
Article Code:	M148990
Colour:	N/s
Material:	Aluminium
Series:	Design, Architectural
Environment:	Indoor
Area contract:	

**OPTICS**

Emission: Indirect/direct Dark Light

**DIMENSIONS**

Length:	(cm) 151
Width:	(cm) 13.2
Height:	(cm) 3.7
Cutout shape:	
Weight:	2.2
Glow Wire Test:	850 °

**LAMPS NOT INCLUDED**

Category:	FLUO
Number:	2
Lbs:	T16
Watt:	80
Socket:	G5
Type:	FDH-80
Luminous Flux (lm):	6150
Colour Rendering:	85
Colour temperature (K):	3000

**Dimensions****LAMP****ELECTRICAL**

Starter:	Electronic Integrated
Voltage:	220V-240V

## ACCESSORIES

---



INTERACTIVE-DALI kit  
Ø86mm, white, recessed.  
Can be connected to a  
max. 11 DALI dimmable  
units. Is operated through  
INTERACTIVE-DALI remote  
control or external push  
button. M074030



INTERACTIVE-DALI remote  
control. M104900



Extension movement  
detector white, recessed.  
To be used when the area  
to be covered is bigger  
than 6,00x5,00m by height  
2,50m. To be connected to  
one of the outputs of the  
INTERACTIVE-DALI  
controller. No extra mains  
connection required.  
M074130