

PRODUCT DATA SHEET

Lost Duo 1214 mm - T16 2x28-54W INTERACTIVE-DALI

**DESIGN BY :**

Ernesto Gismondi

MATERIALS :

Aluminium

DESCRIPTION :

Single pendant with direct-indirect lighting using 54W and 80W T16 fluorescent light source. 2 versions: lost (1xT16) and lost duo (2xT16). Dark light optics with lateral aluminium reflectors. Aluminium central profile (lost duo). End caps in translucent injection moulded polycarbonate. Light output ratio: 66%. Light distribution: 55% indirect and 45% direct. Electronic control gear, with or without dimming (DALI-SWITCHDIM). Luminaire comes complete with quick-adjustment steel cables, ceiling surface plate and power cable. Complies with standard EN60598-1 and other specific standards.

LOST DUO

For use with 2x54W or 2x80W T16. Interactive-DALI system, combining a movement detector and a daylight sensor for auto-regulation in relation to people presence and variations in daylight. Emergency lighting.

Light emission

Indirect/direct Dark Light



TECHNICAL DATA SHEET

Features

Product name:	Lost Duo 1214 mm - T16 2x28-54W INTERACTIVE-DALI
Article Code:	M148892
Colour:	N/s
Material:	Aluminium
Series:	Design, Architectural
Environment:	Indoor
Area contract:	

Dimensions**OPTICS**

Emission: Indirect/direct Dark Light

DIMENSIONS

Length:	(cm) 121
Width:	(cm) 13.2
Height:	(cm) 3.7
Cutout shape:	
Weight:	1.8
Glow Wire Test:	850 °

LAMPS NOT INCLUDED

Category:	FLUO
Number:	2
Lbs:	T16
Watt:	54
Socket:	G5
Type:	FDH-54
Luminous Flux (lm):	4450
Colour Rendering:	85
Colour temperature (K):	3000
Duration (h):	20000

LAMP**ELECTRICAL**

Starter:	INTERACTIVE-DALI Integrated
Voltage:	220V-240V

ACCESSORIES



INTERACTIVE-DALI kit
Ø86mm, white, recessed.
Can be connected to a
max. 11 DALI dimmable
units. Is operated through
INTERACTIVE-DALI remote
control or external push
button. M074030



INTERACTIVE-DALI remote
control. M104900



Extension movement
detector white, recessed.
To be used when the area
to be covered is bigger
than 6,00x5,00m by height
2,50m. To be connected to
one of the outputs of the
INTERACTIVE-DALI
controller. No extra mains
connection required.
M074130