

BEGA**84 368**

Floodlight

IP 65

Project · Reference number

Date

Product data sheet**Application**

Portable floodlight with connecting cable and power plug for efficient illumination of gardens. The floodlight can be placed on lawns, soil as well as on paths and terraces.

Product description

Floodlight made of glass-fibre reinforced polyamide
 Clear safety glass
 Silicone gasket
 Reflector surface made of pure aluminium
 Swivel range $-15^{\circ}/+90^{\circ}$
 No tools are needed to adjust the operating position
 Factory wired with 5 m cable H05RN-F 3 G 1[□] with power plug which is partly rollable under the luminaire
 LED power supply unit
 220-240 V \sim 50-60 Hz
 Safety class I
 Protection class safety plug IP X4
 Protected against splash water
 Protection class luminaire IP 65
 Dusttight and protected against water jets
CE – Conformity mark
 Weight: 1.0 kg

Inrush current

Inrush current: 14 A / 130 μ s
 Maximum number of luminaires of this type per miniature circuit breaker:
 B10A: 29 luminaires
 B16A: 48 luminaires
 C10A: 46 luminaires
 C16A: 76 luminaires

Lamp

Module connected wattage	5 W
Luminaire connected wattage	6.5 W
Rated temperature	$t_a = 25^{\circ}\text{C}$
Ambient temperature	$t_{a\text{max}} = 35^{\circ}\text{C}$

On request we can offer you modifications for environments with higher temperatures as a customized product.


84 368 K3

Module designation	LED-0753/930
Colour temperature	3000 K
Colour rendering index	CRI > 90
Module luminous flux	590 lm
Luminaire luminous flux	440 lm
Luminaire luminous efficiency	67,7 lm/W

Lifetime of the LED

Ambient temperature $t_a = 25^{\circ}\text{C}$
 – at 350,000h: L70B50

max. ambient temperature $t_a = 35^{\circ}\text{C}$
 – at 290,000h: L70B50

**Lighting technology**

Half beam angle 36°
 Luminaire data for the light planning program DIALux for outdoor lighting, street lighting and interior lighting as well as luminaire data in EULUMDAT and IES format are available on our website www.bega.com.

Accessories

For the electrical connection, we recommend the BEGA connecting pillars with safety sockets. You can find them on our website at www.bega.com.