Design Atelier Bellini

iGuzzini


Wall-mounted emergency indication luminaire - LED - Centralized Testing

Last information update: May 2018

Technical description

Product code **MU38**

Luminaire with LED lamp for indicating escape routes. Wall-mounted in a parallel cantilever position. White finish, shaped sheet steel component holder structure. Permanent operation (always on - SA); in event of blackouts guarantees an emergency autonomy of 3 hours with the battery fully charged. Sign visible from a distance of 25m (in compliance with UNI EN 1838). Luminaires with centralized testing are equipped with an interface circuit that can interact with the external accessory control unit (code no. MXS9). In the event of a fault or malfunctioning the devices involved are indicated on the control unit display by means of a specific identification number. For explanations of all the operating warning lamp functions, see the instructions sheet. Ni-Cd battery with 24 hour recharge time. Indicator screens available with a separate code (pictogram design L22).



Installation

Wall-mounted - by removing the cover safety guard and fixing the support base to the surface using screws and screw anchors (not supplied); the luminaire structure is then mounted on the base.

Dimension (mm) 360x55x95

Colour

White (01)

Mounting wall surface

Wiring

Inside the structure - the protection panel must be removed and the necessary connections made on the standard terminals.

Notes

Inhibition Mode Function (only for versions with centralized testing): allows the system to be switched off even for long periods. The emergency system must be reactivated using the control unit code no. MXS9.



Product characteristics

Total lighting output [Lm]: 35 Total power [W]: 1 Luminous efficacy [Lm/W]: 35.0 Number of optical assemblies: 1

Optical assembly Characteristics Type 1 Light Output Ratio (L.O.R.) [%]: /

Lamp code: / ZVEI Code: LED Nominal power [W]: 1 Nominal luminous [Lm]: 35 Lamp maximum intensity [cd]: / Beam angle [°]: /

Total luminous flux at or above an angle of 90° [Lm]: 0 Emergency luminous flux [Lm]: / Voltage [V]: -

Number of lamps for optical assembly: 1 Socket: / Ballast losses [W]: / Colour temperature [K]: 4000 CRI: 80 Wavelength [Nm]: / MacAdam Step: /

MU38_EN 1/1