

WALL SYSTEM BACK 2 REMOTE POWER SUPPLY

Number of heads

Mounting Wall surface

Top LED 8W 553 Im 3000K CRI 80 Lamps description

Luminaire luminous flux See reference number

Voltage (V) 24 **Environment** Indoor

OPTICAL

Aiming Adjustable 70° Beam angle

ELECTRICAL

Transformer availability Separate item Transformer mounting Remote Transformer type Electronic **Emergency** Without **Insulation class** Class III

PHYSICAL

Construction material Aluminium 0,37 Weight (kg)






Wall System Back 2 Remote Power Supply

designed by Antonio Citterio

Indirect-illumination lighting device for installation flush with the wall with remote driver.

F9466057 - 407lm

Chrome




CERTIFICATIONS











Flos.architectural@flos.com www.flos.com



Wall System Back 2 Remote Power Supply . Accessories

Power Supply





60.8079

Constant Current Power Supply for LED. 24V/8W

Electronic transformer with constant voltage (24V) for LED. 220/240V, 50/60Hz.

Maximum lenght of 1.5 mm2 secundary conductor (m): 5

Wall System Back 2 Remote Power Supply . Lamps



Top LED

Lamp category:

LED

Socket:

Special base

Lamp type:

Top LED



Wall System Back 2 Remote Power Supply


designed by Antonio Citterio

Indirect-illumination lighting device for installation flush with the wall with remote driver.



F9466057 - 407lm

Chrome




CERTIFICATIONS











Flos.architectural@flos.com www.flos.com