

Faretti

D27 F62 01 Tondo

Luca Scacchetti

Satin 24% lead crystal diffuser.

tipology



suggested bulb and options (n.i.)

| | |
|---------------|-----------|
| A10704C10 | A10705C01 |
| GU5,3 | GU5,3 |
| 1x50W | 1x4W |
| HRGS | |
| 38° | |
| η 90,20% | |



volume - weight

0,009 m³ - 1,10 Kg

technical information



accessories included

notes

accessories not included

- A22101 Electronic transformer 60W 230/12V (min 10W-max 60W) (max 1 spot)
- A22201 Electronic transformer 150W 230/12V (min 75W-max 150W) (min 2 max 3 spots)
- A22202 Electronic transformer 200W 230/12V (min 100W-max 200W) (min 2 max 4 spots)
- A22002 Toroidal transformer 230/12V 50W IP67 (max 1 spot)

