

APPS EMERGENCY 90 DIR

Lamps description LED Array 4W 350 lm 4000K CRI 80

Environment Indoor

OPTICAL

Aiming Fixed

ELECTRICAL

Control gear availability Included
Control gear type Electronic
Emergency Included 4 hours

Insulation class Class II

PHYSICAL

Weight (kg) 1,5






APPS Emergency 90 DIR designed by Jorge Herrera

Recessed emergency sign luminaire for indoor application. Power supply source and emergency gear included. 4-hour autonomy, 80% Flow.

SA.5071.3.076 White



CERTIFICATIONS









info@flos.it www.flos.com



APPS Emergency 90 DIR . Lamps




LED Array
Lamp category:
LED
Lamp type:
LED Array



APPS Emergency 90 DIR designed by Jorge Herrera

Recessed emergency sign luminaire for indoor application. Power supply source and emergency gear included. 4-hour autonomy, 80% Flow.

SA.5071.3.076 White



CERTIFICATIONS









www.flos.com