

#### **PURE I DOWNLIGHT I-10V**

Number of heads

Mounting Ceiling recessed

Lamps descriptionPhosphor LED 13,6W 1490 lm 3000K CRI 80Luminaire luminous fluxExtreme Cut-off. See reference number

Voltage (V) 220/240 Environment Indoor

Notes To be completed with installation frame. Available as

accessory element. Must be ordered separately.

#### **OPTICAL**

Light controller descriptionReflectorAimingAdjustableLight distribution symmetrySymmetricBeam angle51° Wide Flood

#### **ELECTRICAL**

Transformer availability Included
Transformer mounting Remote

Transformer type Electronic dimmable I-10V

EmergencyWithoutInsulation classClass II

#### **PHYSICAL**

Cutout diameter (mm) 135 Spot diameter (mm) 86

Construction material Aluminium
Weight (kg) 0,96






Pure I Downlight I-10V designed by Knud Holscher

LED recessed downlight. Phosphor LED module integrated. Remote electronic transformer 220/240V included.

09.1637.30C1V - 1075lm White
09.1637.02C1V - 1075lm Grey
09.1637.14C1V - 1075lm Black



#### **CERTIFICATIONS**

















Flos.architectural@flos.com www.flos.com



# Pure I Downlight I-I0V. Accessories

# **Optical**









08.8166.14

Holding ring

08.8163.68

Elliptical lens

Elliptical light distribution lens in 4 mm thick tempered glass. 08.8169.14

Honeycomb

"Honeycomb" anti-glare screen: in thin, blackpainted aluminium sheets.

Pure I Downlight I-I0V designed by Knud Holscher


LED recessed downlight. Phosphor LED module integrated. Remote electronic transformer 220/240V included.

09.1637.30CIV - 1075lm White 09.1637.02CIV - 1075lm Grey 09.1637.14C1V - 1075lm Black









08.8160.64.OD

Blue filter

Blue filter

08.8160.65.OD


Sky blue filter

Sky blue filter

08.8160.66.OD

**Amber filter** 

Amber filter









**CERTIFICATIONS** 



60°







08.8160.67.OD

Red filter

Red filter

08.8160.98.OD

U.V. filter

U.V. filter

08.8160.68

I.R. filter

I.R. filter

360°






Flos.architectural@flos.com www.flos.com



# Pure I Downlight I-I0V. Accessories









08.8160.69

**Hot Light** 

Hot Light

08.8160.CL

Cold light filter

Cold light filter

08.8160.DL

**Daylight filter** 

Daylight filter


Pure I Downlight I-I0V designed by Knud Holscher

LED recessed downlight. Phosphor LED module integrated. Remote electronic transformer 220/240V included.









09.1637.14C1V - 1075lm Black



08.8160.ND

Neodimium






08.8232.30



08.8232.02



08.8232.14



#### Flood lens

Flood lens made in press glass.

# Pure I Pro external ring accessory

Pure I Pro external ring accessory. Only for halogen and halide lamps, consult for LED version

# CERTIFICATIONS


















Flos.architectural@flos.com www.flos.com



# Pure I Downlight I-I0V. Accessories

### Mounting







08.8152.00

Installation Frame For No Trim

Installation frame for Pure I Downlight No Trim.

**HOW TO ORDER** 

08.8149.30

08.8149.02

08.8149.14

Installation Frame For Trim


Installation frame for Pure I Downlight Trim.



Pure I Downlight I-10V designed by Knud Holscher

LED recessed downlight. Phosphor LED module integrated. Remote electronic transformer 220/240V included.

09.1637.30C1V - 1075lm White
09.1637.02C1V - 1075lm Grey
09.1637.14C1V - 1075lm Black



# Pure I Downlight I-I0V . Lamps



Phosphor LED Lamp category:

LED

Lamp type:

Phosphor LED

#### **CERTIFICATIONS**

















Flos.architectural@flos.com www.flos.com