


Vega S100

Vega S100 is a square lamp characterized by a directional LED projector ideal for creating limited scenarios. The lamp can be installed using the Contatto fixing and power supply kit, or, in the wireless version, using the K-Wireless panel.

-  **Magnetic fixing**
-  **Light**
-  **InDoor**



Vega S100

Supply voltage	12 VDC
Max. current	2 A
Technology	LED
Temperature	<input checked="" type="radio"/> 3000K <input type="radio"/> 4000K
Optic	POINTED
CRI	90
Use	INDOOR

Contatto version (page 60)	<input checked="" type="radio"/> 3000K	<input type="radio"/> 4000K
Power	3,75 W	3,75 W
Lumen	400	420
Touch control	Yes	Yes

Wireless version (from page 61)	<input checked="" type="radio"/> 3000K	<input type="radio"/> 4000K
Power	3 W	3 W
Lumen	330	350

Code	Color	Temperature	Optic	Installation
VEG-S	White = B	3000°K = 3K	10° = 1	Contatto = C
	Black = N	4000°K = 4K	30° = 3	Wireless = W